





## MIPRO ACT-828 (DANTE)

## **TECHNICAL DETAILS**

| Device type               | Receiver  |
|---------------------------|---|
| Operating frequency (MHz) | 540 ~ 604 (UHF, 5F)                                   |
| Frequency response (Hz)   | 20 ~ 20000  |
| THD (%)                   | 0.03  |
| Sensitivity               | 12dB∄V  |
| Signal-to-noise ratio     | 2115dBA   |
| Connectors                | 1 x Dante Interface (Cat5/5e/6)                       |
| Connectors                | 2 x 6.3mm jack (Unbalanced output)                    |
| Connectors                | 2 x RJ11 (Mipro-DVU)                                  |
| Connectors                | 1 x 6.3mm jack (Phones)                               |
| Connectors                | 2 x XLR (3-pin, Balanced output)                      |
| Connectors                | $2 \times AES3id$ (S/PDIF, Unbalanced digital output) |
| Image rejection (dB)      | 85  |
| Width (mm)                | 420   |
| Height (mm)               | 44.45 (1U)  |
| Depth (mm)                | 245   |
| Net weight (kg)           | 2.2   |
|                           |   |

## PRODUCT DESCRIPTION

SQM Multimedia Support offers a professional digital receiver ACT-828 with the Dante interface by Mipro. The two-channel receiver carries frequencies in the range of 20Hz-20kHz (-2dB) and works in the 64MHz bandwidth (UHF 5F, from 540 to 604MHz) with the possibility of changing the channel every 25kHz. ACT-828 is equipped with two antennas.

The 24-bit receiver features 2.7-millisecond latency, a total harmonic distortion factor of 0.03% (1kHz) and sampling at 44.1kHz.

The front panel of ACT-828 is equipped with two VFD displays that provide information about the parameters of a given channel, two knobs that control the displays' content and buttons that synchronize the transmitter with the receiver. In addition, on the left, there is a 6.3-mm headphone jack, volume knob and LED that indicates the selected channel.

The rear panel of the receiver is divided into two output sections, for which one three-pole XLR connector (symmetrical), 6.3-mm jack connector











(unbalanced) and AES3id digital connector (S/PDIF, also unbalanced) are assigned. Each section also has two switches - one for disconnecting or connecting the ground, and the other for changing the mode from linear to a microphone or vice versa.

In addition, there are two RJ11 connectors and a Dante interface - a plug&play protocol that provides uncompressed, multi-channel, low-latency digital signal based on Ethernet. The devices must be connected via a Cat5, Cat5e or Cat6 cable.

An additional advantage is a possibility of parallel DC power supply (12-15V) and dimensions that allow installation in a rack cabinet (1U). SQM Rental House also encourages you to check the Mipro ACT-80T transmitter and Mipro ACT-80H microphone, with which the Mipro ACT-828-Dante digital receiver works perfectly.

## Product link:

https://rentalhouse.sqm.eu/gb/accessories/974-mipro-act-828-dante.html