

ALLEN & HEATH ZED 6



TECHNICAL DETAILS

Mixer category	Audio
Mixer type	Analog
Channels	6
Channels	2 (Stereo)
Frequency response (Hz)	10 ~ 20000 (+0.5/-1dB)
Headroom (dB)	18
Connectors	1 x 6.25mm jack (Phones)
Connectors	2 x XLR (Input, 3-pin)
Connectors	2 x XLR (3-pin, Main output)
Connectors	4 x 6.25mm jack (Stereo line input)
Connectors	2 x 6.25mm jack (Line input)
Power supply	100-240V AC; 50-60Hz
Width (mm)	249
Height (mm)	88.9
Depth (mm)	236.4
Net weight (kg)	1.3



PRODUCT DESCRIPTION

The ZED 6 is a compact 6-channel analog mixer from Allen & Heath.

The mixer features two mic/line inputs on XLR (3-pin) or TRS (6.25mm jack) jacks, two stereo inputs on TRS jacks, two XLR symmetrical outputs and a headphone output (6.25mm jack). The high impedance on the jack inputs for the mono channels, for example, allows a guitar to be plugged directly into the unit, without the need to use a DI-box.

The Allen & Heath ZED 6 is equipped with a GSPre preamplifier, which guarantees very low noise and high headroom values. The compact ZED 6 also features a high-pass filter, a 60-millimeter attenuator for the master mix and a two-band equalizer. The mixer can be powered by Phantom (48V).

Rent the Allen & Heath ZED 6 analog mixer from SQM Rental House for your event!

Product link:

<https://rentalhouse.sqm.eu/gb/audio-mixers/1552-allen-heath-zed-6.html>