







## **CHAMSYS QUICKQ 20**

## **TECHNICAL DETAILS**

Standard	DMX512
Mixer category	Light
Mixer type	Digital
Channels	1024
Connectors	2 x 3.5mm jack (Audio input/output)
Connectors	2 x USB-A
Connectors	1 x HDMI (Output)
Connectors	2 x DMX (XLR output, 5-pin)
Connectors	1 x Ethernet (RJ45)
Connectors	2 x MIDI (Input/output, DIN-5)
Width (mm)	565
Height (mm)	106
Depth (mm)	350
Net weight (kg)	5.2
Set contains	1 x Dust cover
Set contains	1 x WiFi antenna
Set contains	Power cord
Set contains	1 x USB desk light
Set contains	1 x Tablet stand
Set contains	Power supply


## PRODUCT DESCRIPTION

QuickQ 20 is a versatile unit in the ChamSys QuickQ series of lighting control consoles, which feature ease of use. This console is ideal for controlling dimmers, LED colour mixing and moving light fixtures. Equipped with a 9.7-inch touchscreen, it offers a smartphone-like interface for easy setup, programming and show operation.

 $The console offers a maximum of 1024 \, DMX \, channels \, and \, supports \, up \, to \, 1024 \, fixtures \, simultaneously. \, It \, allows \, the \, creation \, of \, up \, to \, 10 \, Cue \, stacks \, and \, 10 \, Cu$ 









Chases. It supports Midi, Midi Timecode and OSC protocols and has an RDM Autopatch function for quick show patching. It comes with a library of more than 30,000 device files and a built-in FX effects generator.

The console automatically recognises and configures RDM-compatible devices and has built-in WIFI for remote connection to the free QuickQ app for iOS, Android and Windows tablets and phones.

The console features intuitive buttons and sliders, simple tools for colour selection and intensity control, and a large touchscreen with zoom and scroll functions. It also offers a simple cue/chase system for show playback. The QuickQ interface, designed specifically for beginners, guides the user through the setup, programming and operation of the console.

Free offline programming software for Mac and Windows is also available, allowing you to program a show on your computer, save it to a flash drive and load it onto the QuickQ console.

Shows created on the QuickQ console are compatible with any MagicQ system, allowing you to later upgrade to ChamSys' more advanced MagicQ consoles.

## Product link:

https://rentalhouse.sqm.eu/gb/consoles/2012-chamsys-quickq-20.html