

## ROLAND V-1HD

### TECHNICAL DETAILS

Video processing	Y:Pb:Pr; 4:2:2; 8-bit
Supported video formats	1080@59.94i; 1080@50i; 1080@59.94p; 1080@50p; 720@59.94p; 720@50p
Transition effects	Cut; Mix (Dissolve/Fam/Nam/Mosaic); Wipe (30 types); Transformer (11 types)
Other effects	Negative; Emboss; Colorize; Colorpass; Posterize; Silhouette; Monocolor; Findedge; Flip
Audio effects	EQ; Delay; Compressor; HPF; Gate; Reverb; Mastering
Connectors	2 x RCA (Audio output)
Connectors	1 x 3.5mm jack (Phones output)
Connectors	1 x HDMI (Preview)
Connectors	4 x HDMI (Input)
Connectors	2 x RCA (Audio input)
Connectors	1 x 3.5mm jack (Mic input)
Connectors	2 x MIDI (Input/output/thru, 5-pin DIN)
Connectors	1 x USB-B
Connectors	1 x HDMI (Output)
Max. power consumption (W)	18
Power supply	AC adaptor
Width (mm)	313
Height (mm)	59
Depth (mm)	102
Net weight (kg)	1.2
Set contains	Power supply

### PRODUCT DESCRIPTION



Roland V-1HD is a professional signal switcher that supports Full HD 1080p, which is ideally suited as a miniature production studio for a mass event organization.

The mixer offers four HDMI inputs that process audio/video signals from many mobile devices, MIDI connectors, USB Type-B port, audio input/output on RCA connectors, as well as two 3.5mm jacks for connecting a microphone and headphones.

The V-1HD offers free adjustment of contrast, color and saturation parameters. It also has a rich palette of compositional effects and image maneuvering effects. The mixer also allows you to mix audio signals.

The Roland V-1HD switch recommended by SQM Rental House is a very intuitive device. In addition to the traditional method, it is also possible to control the switcher from the V-1HD Remote software on a computer.

Product link:

<https://rentalhouse.sqm.eu/gb/mixers/213-roland-v-1hd.html>