

APART MA65

TECHNICAL DETAILS



Frequency range (Hz)	60 ~ 18000
Zones	1
Signal-to-noise ratio	-67dB
Min. output impedance (Ω)	8
Continuous power (W)	65
Connectors	2 x RCA (Line output)
Connectors	1 x DIN5/F
Connectors	3 x 6.3mm TRS
Connectors	4 x RCA (Line input)
Connectors	3 x XLR/F (3-pin, Phantom)
Connectors	Euroblock
Connectors	2 x RCA (Pre Out/Amp In)
Power supply	24V DC
Power supply	115-230V AC
Width (mm)	272
Height (mm)	88 (2U)
Depth (mm)	297
Net weight (kg)	6.4

PRODUCT DESCRIPTION

SQM Rental House recommends the Apart Audio MA65 (Biamp) compact mixing amplifier, which is dedicated to 100-volt installations.

The rear panel of the Apart Audio MA65 amplifier has two microphone inputs [(MIC1 - XLR/DIN5 and MIC2 - XLR/6.3mm)], one microphone-line (MIC3) and one line (MIC4 - RCA). In addition, there are RCA outputs, Euroblock terminal, IEC power socket, and a ground terminal. The front panel offers a priority input (MIC1 - 6.3mm), four knobs to control the volume of 1-4 inputs, a treble control knob and a knob for bass.

The MA65 has a two-step VOX priority system, thanks to which activation of the MIC1 priority input mutes all others.

The compact amplifier provides 65W of power, and its additional advantage is the ability to work at 24-volt, e.g. in the emergency power supply. With the use of a mounting bracket, the MA65 can be installed in a 19-inch rack.

Product link:

<https://rentalhouse.sqm.eu/gb/audio-mixers/215-apart-ma65.html>