

QSC TOUCHMIX-16

TECHNICAL DETAILS



Mixer category	Audio
Mixer type	Digital
Channels	4 (Stereo)
Channels	16 (Mono, mic/line)
Frequency response (Hz)	20 ~ 20000 (+/-0.5dB)
THD (%)	≈0.005 (+4dBu; 20Hz~20kHz)
Headroom (dB)	N/A
Connectors	12 x XLR (3-pin, Mic balanced input)
Connectors	2 x 6.3mm TRS (Stereo line input)
Connectors	2 x 6.3mm TRS (Phones/Monitors)
Connectors	1 x XLR (3-pin, Talkback input)
Connectors	2 x XLR (3-pin, Main output)
Connectors	4 x Combo XLR/6.3mm jack (Mic/line balanced input)
Connectors	2 x 6.3mm TRS (AUX line output)
Connectors	2 x USB-A 3.0
Connectors	6 x XLR (3-pin, AUX output)
Power supply	100-240V AC; 50-60Hz
Width (mm)	360
Height (mm)	58
Depth (mm)	291
Net weight (kg)	2.98

PRODUCT DESCRIPTION

TouchMix-16 is a digital audio mixer by QSC. The device has sixteen monophonic channels and four stereo channels. In addition, a four-band full parametric equalizer, adjustable high- (20Hz~20kHz, +/-15dB) and low-pass filters (1kHz~20kHz, +/-15dB) are available on all channels.

TouchMix-16 consists of 12 XLR microphone and 4 XLR/6.3mm combo microphone/line mono inputs. Stereo inputs are presented in the form of two 6.3-mm TRS sockets (two channels per one jack). In addition, the user has at its disposal stereo Aux outputs and a Cue section for connecting headphones and a signal monitor.

The rear panel offers two USB 3.0 Type-A connectors, an XLR talkback microphone input, two main outputs, and six mono (unbalanced) Aux outputs. The QSC TouchMix-16 is mainly operated via the analog trim knobs, main knob and the 7-inch LCD screen.

Further functionalities available in the compact mixer are four stereo effects, eight mute and DCA groups and pitch correction for a specific input channel. The QSC TouchMix-16 mixer is available at SQM Rental House!

Product link:

<https://rentalhouse.sqm.eu/gb/audio-mixers/36-qsc-touchmix-16.html>