

SHURE BETA 98H/C

TECHNICAL DETAILS

Device type	Microphone
Max. SPL (dB; @1m)	155
Frequency response (Hz)	20 ~ 20000
Dynamic range (dB)	124
Sensitivity	-56dBV/Pa (1.6mV)
Signal-to-noise ratio	63dB
Connectors	1 x XLR (3-pin, Output)
Output impedance (Ω)	150
Microphone type	Condenser
Polar pattern	Cardioid
Cable length (cm)	300



PRODUCT DESCRIPTION

The Shure BETA 98H/C is a compact instrument microphone with a dedicated cardioid characteristic for high levels of sensitivity before feedback and noise immunity.

The dynamic microphone features a preamplifier circuit that corrects the line operation over the entire frequency range. The Shure BETA 98H/C is suitable for wind and percussion instruments, mainly due to its ability to work with high sound pressure levels, and the frequency response used enables natural sound reproduction.

The BETA 98H/C is equipped with a gooseneck, a 3-meter flexible cable with preamplifier (XLR) and a mounting clip, which is great for duets with the previously mentioned wind and percussion instruments - both in the studio and stage environment. Rent the Shure BETA 98H/C microphone at SQM Rental House!

Product link:

<https://rentalhouse.sqm.eu/gb/microphones/1517-shure-beta-98hc.html>