






PRODUCT NAME

# SHURE BETA 58A

DESCRIPTION

The Shure BETA 58A is a dynamic vocal microphone with super-cardioid characteristics, an enhanced mid-range and a clipped bass for proximity effect control.

The frequency response of the BETA 58A is tailored for excellent vocal reproduction. It also provides a maximum level of sensitivity before feedback occurs and excellent suppression of off-axis sounds. The equipment uses a neodymium magnet, which allows for a better useful output signal-to-noise ratio. The Shure BETA 58A is also insensitive to varying load impedance.

The Shure BETA 58A vocal microphone will be great for both studio recordings and stage appearances. Check out the microphone at SQM Rental House!

## SPECIFICATIONS

| | |
|---|---|
| **Device type** | Microphone |
| **Frequency response (Hz)** | 50 ~ 16000 |
| **Sensitivity** | -51.5dBV/Pa (2.6mV) |
| **Output impedance (Ω)** | 150 |
| **Microphone type** | Dynamic |
| **Polar pattern** | Supercardioid |
| **Microphone diameter (mm)** | 50 (Capsule) |
| **Height (mm)** | 160 |
| **Connectors** | 1 x XLR (3-pin, Output) |
| **Net weight (kg)** | 0.28 |