






TECHNICAL DETAILS







PRODUCT DESCRIPTION

SQM Multimedia Support proposes a PA 60 USB/R mixing amplifier with a built-in audio player from WorkPro. The amplifier works great with low impedance speakers (minimum 8 ohms) and high impedance installations (25V, 70V, and 100V). The continuous power of the amplifier reaches 60W, and







the peak value is 90W. The built-in player supports MP3/WMA files.

The amplifier has two microphone inputs (XLR/6.3mm and XLR/DIN5), microphone-line input (XLR/6.3mm) and two unbalanced line inputs ($4 \times RCA$, AUX1, and AUX2). The rear panel also has a terminal for two-wire speaker cables and 24V DC emergency power supply. There is also a preamplifier output/power amplifier input (RCA Pre Out/Amp In socket) and a recording output ($2 \times RCA$, Tape Out).

The front panel of PA 60 USB/R allows you to connect a microphone with a priority function (MIC 1) and is equipped with an LED diode that informs about the output power parameters. The panel also has knobs for adjusting the bass and treble, as well as signal level regulators for each of the inputs and a general Master knob. To play files, connect an external device to the SD/MMC card slot or USB-A slot (up to 32GB). Played multimedia can be controlled via a 9-button interface with an LED screen.

WorkPro PA 60 USB/R is designed for both use as a free-standing device on the base, and for mounting in a rack (height of 2U).

Product link:

https://rentalhouse.sqm.eu/gb/accessories/517-workpro-pa-602-usbr.html